

# Operation Manual

Led Strobe can make colorful and dynamic light scenery effects. It is widely applied to entertainment hall, club and stage

## A Specification

1. Weight: 4.9kg
2. Size: 46\*20\*12.5cm
3. Power input: AC 120V/240V, 60Hz/50Hz
4. Wattage: 34W
5. LEDs: 252PCS RGB (52 RED, 116GREEN, 84 BLUE)
6. 3PIN female XLR socket and 3PIN male XLR socket
7. Built-in microphone



## B. Function description



Mode	Dip10 dip9	Dip8 dip7 dip6 dip5 dip4 dip3 dip2 dip1	Function
Auto Run (Master projector)	0 0	X X 0 0 0 0 0 0	Color changing and color fading Select running speed via dip7, dip8
		0 0 X X X X X X	Static color and flash Select static color via dip1~dip3 (separately for R.G.B) select flash speed via Dip4~dip6
Sound activated (Master projector)	0 1	X X X X X X X X	Change color via sound activated
DMX	1 X	X X X X X X X X	DMX mode CH1→R CH2→G CH3→B CH4→Dimmer and flash
Other	1 0	0 0 0 0 0 0 0 1	1. DMX address is 1 when in DMX mode 2. As Slave projector when in M/S mode
	1 0	0 0 0 0 0 0 0 0	Black out

## DMX Value/Function

CHANNEL	VALUE	FUNCTION
CH1	000-255	RED
CH2	000-255	GREEN
CH3	000-255	BLUE
CH4	000-189	DIMMER
	190-250	FLASH
	251-255	NO FUNCTION